

# Diesel Generator Set Model DFGB 60 Hz

**600 kW, 750 kVA Standby  
545 kW, 681 kVA Prime**



## Description

The Cummins Power Generation DF-series commercial generator set is a fully integrated power generation system providing optimum performance, reliability, and versatility for stationary standby or prime power applications.

A primary feature of the DF GenSet is strong motor-starting capability and fast recovery from transient load changes. The torque-matched system includes a heavy-duty Cummins 4-cycle diesel engine, an AC alternator with high motor-starting kVA capacity, and an electronic voltage regulator with three-phase sensing for precise regulation under steady-state or transient loads. The DF GenSet accepts 100% of the nameplate standby rating in one step, in compliance with NFPA110 requirements.

The standard PowerCommand<sup>®</sup> digital electronic control is an integrated system that combines engine and alternator controls for high reliability and optimum GenSet performance.

Optional coolant heaters improve starting in extreme operating conditions. A wide range of options, accessories, and services are available, allowing configuration to your specific power generation needs.

Every production unit is factory tested at rated load and power factor. This testing includes demonstration of rated power and single-step rated load pickup. Cummins Power Generation manufacturing facilities are registered to ISO9001 quality standards emphasizing our commitment to high quality in the design, manufacture, and support of our products. The generator set is CSA certified and is available as UL 2200 Listed. The PowerCommand control is UL 508 Listed.

All Cummins Power Generation systems are backed by a comprehensive warranty program and supported by a worldwide network of 170 distributors and service branches to assist you with warranty, service, parts, and planned maintenance support.

## Features

**UL Listed Generator Set** - The complete generator set assembly is available Listed to UL 2200.

**Cummins Heavy-Duty Engine** - Rugged 4-cycle industrial diesel delivers reliable power, low emissions, and fast response to load changes.

**Permanent Magnet Generator (PMG)** - Offers enhanced motor starting and fault clearing short circuit capability.

**Alternator** - Several alternator sizes offer selectable motor starting capability with low reactance 2/3 pitch windings; low waveform distortion with non-linear loads, fault clearing short-circuit capability, and class H insulation.

**Control System** - The PowerCommand electronic control is standard equipment and provides total genset system integration, including automatic remote starting/stopping, precise frequency and voltage regulation, alarm and status message display, AmpSentry<sup>™</sup> protection, output metering, auto-shutdown at fault detection, and NFPA 110 compliance. PowerCommand control is listed to UL508.

**Cooling System** - Provides reliable running at rated power in ambient temperatures through 50°C.

**Structural Steel Skid Base** - Robust skid base supports the engine, alternator, and radiator.

**E-Coat Finish** - Dual electro-deposition paint system provides high resistance to scratches, corrosion, or fading.

**Enclosures** - Optional weather-protective and sound-attenuated enclosures are available.

**Certifications** - Generator sets are designed, manufactured, tested, and certified to relevant UL, NFPA, ISO, IEC, and CSA standards.

**Warranty and Service** - Backed by a comprehensive warranty and world wide distributor network.

## Generator Set

The general specifications provide representative configuration details. Consult the outline drawing for installation design.

### Specifications – General

See outline drawing 500-3477 installation design specifications.

|  |   |
|--|---|
| Unit Width, in (mm)                      | 72.1 (1830)   |
| Unit Height, in (mm)                     | 88.2 (2242)   |
| Unit Length, in (mm)                     | 169.5 (4305)  |
| Unit Dry Weight, lb (kg)                 | 13600 (6169)  |
| Unit Wet Weight, lb (kg)                 | 14160 (6423)  |
| Rated Speed, rpm                         | 1800  |
| Voltage Regulation, No Load to Full Load | ±0.5%   |
| Random Voltage Variation                 | ±0.5%   |
| Frequency Regulation                     | Isochronous   |
| Random Frequency Variation               | ±0.25%  |
| Radio Frequency Interference             | IEC 801.2, Level 4 Electrostatic Discharge<br>IEC 801.3, Level 3 Radiated Susceptibility<br>IEC 801.4, Level 4 Electrical Fast Transients<br>IEC 801.5, Level 5 Voltage Surge Immunity<br>MIL STD 461C, Part 9 Radiated Emissions (EMI) |

| Cooling                                     | Standby        | Prime          |
|---|----------------|----------------|
| Fan Load, HP (kW)                           | 30.0 (22.4)    | 30.0 (22.4)    |
| Coolant Capacity with radiator, US Gal (L)  | 44.0 (166.5)   | 44.0 (166.5)   |
| Coolant Flow Rate, Gal/min (L/min)          | 236.0 (893.3)  | 236.0 (893.3)  |
| Heat Rejection To Coolant, Btu/min (MJ/min) | 26065.0 (27.6) | 20985.0 (22.2) |
| Heat Radiated To Room, Btu/min (MJ/min)     | 7790.0 (8.3)   | 6920.0 (7.3)   |
| Maximum Coolant Friction Head, psi (kPa)    | 10.0 (68.9)    | 10.0 (68.9)    |
| Maximum Coolant Static Head, ft (m)         | 60.0 (18.3)    | 60.0 (18.3)    |

| Air  |                  |                  |
|--|------------------|------------------|
| Combustion Air, scfm (m <sup>3</sup> /min)         | 2280.0 (64.5)    | 2065.0 (58.4)    |
| Alternator Cooling Air, scfm (m <sup>3</sup> /min) | 4156.0 (117.6)   | 4156.0 (117.6)   |
| Radiator Cooling Air, scfm (m <sup>3</sup> /min)   | 42000.0 (1188.6) | 42000.0 (1188.6) |
| Max. Static Restriction, in H <sub>2</sub> O (Pa)  | 0.25 (62.25)     | 0.25 (62.25)     |

### Rating Definitions

**Standby Rating based on:** Applicable for supplying emergency power for the duration of normal power interruption. No sustained overload capability is available for this rating. (Equivalent to Fuel Stop Power in accordance with ISO3046, AS2789, DIN6271 and BS5514). Nominally rated.

**Prime (Unlimited Running Time) Rating based on:** Applicable for supplying power in lieu of commercially purchased power. Prime power is the maximum power available at a variable load for an unlimited number of hours. A 10% overload capability is available for limited time. (Equivalent to Prime Power in accordance with ISO8528 and Overload Power in accordance with ISO3046, AS2789, DIN6271, and BS5514). This rating is not applicable to all generator set models.

**Base Load (Continuous) Rating based on:** Applicable for supplying power continuously to a constant load up to the full output rating for unlimited hours. No sustained overload capability is available for this rating. Consult authorized distributor for rating. (Equivalent to Continuous Power in accordance with ISO8528, ISO3046, AS2789, DIN6271, and BS5514). This rating is not applicable to all generator set models.

### Site Derating Factors

Rated power available up to 4600 ft (1403 m) at ambient temperatures up to 104°F (40°C). Above 4600 ft (1403 m), derate at 4% per 1000 ft (305 m) and 1% per 10°F (2% per 11°C) above 104°F (40°C).

# Engine

Cummins heavy duty diesel engines use advanced combustion technology for reliable and stable power, low emissions, and fast response to sudden load changes.

Electronic governing provides precise speed regulation, especially useful for applications requiring constant (isochronous) frequency regulation such as Uninterruptible Power Supply (UPS) systems, non-linear loads, or sensitive electronic loads. Optional coolant heaters are recommended for all emergency standby installations or for any application requiring fast load acceptance after start-up.

## Specifications – Engine

|  |   |
|--|---|
| <b>Base Engine</b>                     | Cummins Model VTA28-G5, Turbocharged and Aftercooled, diesel-fueled |
| <b>Displacement in<sup>3</sup> (L)</b> | 1710.0 (28.0)   |
| <b>Overspeed Limit, rpm</b>            | 2100 ±50  |
| <b>Regenerative Power, kW</b>          | 105.00  |
| <b>Cylinder Block Configuration</b>    | Cast iron with replaceable wet cylinder liners, 40°V 12 cylinder    |
| <b>Battery Capacity</b>                | 660 amps minimum at ambient temperature of 32°F (0°C)               |
| <b>Battery Charging Alternator</b>     | 55 amps   |
| <b>Starting Voltage</b>                | 24-volt, negative ground  |
| <b>Lube Oil Filter Types</b>           | Three spin-on, full flow  |
| <b>Standard Cooling System</b>         | 122°F (50°C) ambient radiator                                       |

| Power Output  |           |      |   |      |      | Standby        |           | Prime          |      |
|---|-----------|------|---|------|------|----------------|-----------|----------------|------|
| Gross Engine Power Output, bhp (kWm)                        |           |      |   |      |      | 900.0 (671.4)  |           | 815.0 (608.0)  |      |
| BMEP at Rated Load, psi (kPa)                               |           |      |   |      |      | 226.0 (1558.2) |           | 206.0 (1420.3) |      |
| Bore, in. (mm)  |           |      |   |      |      | 5.50 (139.7)   |           | 5.50 (139.7)   |      |
| Stroke, in. (mm)  |           |      |   |      |      | 6.00 (152.4)   |           | 6.00 (152.4)   |      |
| Piston Speed, ft/min (m/s)                                  |           |      |   |      |      | 1800.0 (9.1)   |           | 1800.0 (9.1)   |      |
| Compression Ratio   |           |      |   |      |      | 13.1:1         |           | 13.1:1         |      |
| Lube Oil Capacity, qt. (L)                                  |           |      |   |      |      | 89.0 (84.2)    |           | 89.0 (84.2)    |      |
| Fuel Flow   |           |      |   |      |      |                |           |                |      |
| Fuel Flow at Rated Load, US Gal/hr (L/hr)                   |           |      |   |      |      | 89.0 (336.9)   |           | 89.0 (336.9)   |      |
| Maximum Inlet Restriction, in. Hg (mm Hg)                   |           |      |   |      |      | 4.0 (101.6)    |           | 4.0 (101.6)    |      |
| Maximum Return Restriction, in. Hg (mm Hg)                  |           |      |   |      |      | 6.5 (165.1)    |           | 6.5 (165.1)    |      |
| Air Cleaner   |           |      |   |      |      |                |           |                |      |
| Maximum Air Cleaner Restriction, in. H <sub>2</sub> O (kPa) |           |      |   |      |      | 25.0 (6.2)     |           | 25.0 (6.2)     |      |
| Exhaust   |           |      |   |      |      |                |           |                |      |
| Exhaust Flow at Rated Load, cfm (m <sup>3</sup> /min)       |           |      |   |      |      | 5040.0 (142.6) |           | 4635.0 (131.2) |      |
| Exhaust Temperature, °F (°C)                                |           |      |   |      |      | 935.0 (501.7)  |           | 885.0 (473.9)  |      |
| Max Back Pressure, in. H <sub>2</sub> O (kPa)               |           |      |   |      |      | 41.0 (10.2)    |           | 41.0 (10.2)    |      |
| Fuel System   |           |      | Direct injection, number 2 diesel fuel; fuel filter; automatic electric fuel shutoff. |      |      |                |           |                |      |
| Fuel Consumption  |           |      | Standby   |      |      |                | Prime     |                |      |
| 60 Hz Ratings, kW (kVA)                                     |           |      | 600 (750)   |      |      |                | 545 (681) |                |      |
|   | Load      | 1/4  | 1/2   | 3/4  | Full | 1/4            | 1/2       | 3/4            | Full |
|   | US Gal/hr | 14.7 | 24.3  | 34.1 | 44.2 | 13.9           | 22.6      | 31.2           | 40.3 |
|   | L/hr      | 56   | 92  | 129  | 167  | 53             | 86        | 118            | 153  |
|   |           |      |   |      |      |                |           |                |      |

## Alternator

Several alternators are available for application flexibility based on the required motor-starting kVA and other requirements. Larger alternator sizes have lower temperature rise for longer life of the alternator insulation system. In addition, larger alternator sizes can provide a cost-effective use of engine power in across-the-line motor-starting applications and can be used to minimize voltage waveform distortion caused by non-linear loads.

Single-bearing alternators couple directly to the engine flywheel with flexible discs for drivetrain reliability and durability. No gear reducers or speed changers are used. Two-thirds pitch windings eliminate third-order harmonic content of the AC voltage waveform and provide the standardization desired for paralleling of generator sets. The standard excitation system is a PMG excited system.

## Alternator Application Notes

**Separately Excited Permanent Magnet Generator (PMG) System** - This standard system uses an integral PMG to supply power to the voltage regulator. A PMG system generally has better motor-starting performance, lower voltage dip upon load application, and better immunity from problems with harmonics in the main alternator output induced by non-linear loads. This system provides improved performance over self-excited regulators in applications that have large transient loads, sensitive electronic loads (especially UPS applications), harmonic content, or that require sustained short-circuit current (sustained 3-phase short circuit current at approximately 3 times rated for 10 seconds).

**Alternator Sizes** - On any given model, various alternator sizes are available to meet individual application needs. Alternator sizes are differentiated by maximum winding temperature rise, at the generator set standby or prime rating, when operated in a 40°C ambient environment. Available temperature rises range from 80°C to 150°C. Not all temperature rise selections are available on all models. Lower temperature rise is accomplished using larger alternators at lower current density. Lower temperature rise alternators have higher motor-starting kVA, lower voltage dip upon load application, and they are generally recommended to limit voltage distortion and heating due to harmonics induced by non-linear loads.

**Alternator Space Heater** - is recommended to inhibit condensation.

## Available Output Voltages

### Three Phase Reconnectable

[ ] 110/190  
[ ] 120/208  
[ ] 127/220  
[ ] 139/240  
[ ] 220/380  
[ ] 240/416  
[ ] 254/440  
[ ] 277/480

### Three Phase Non-Reconnectable

[ ] 277/480  
[ ] 347/600

# Specifications – Alternator

|  |  |
|--|--|
| <b>Design</b>                                | Brushless, 4 pole, drip proof revolving field                        |
| <b>Stator</b>                                | 2/3 pitch  |
| <b>Rotor</b>                                 | Direct coupled by flexible disc                                      |
| <b>Insulation System</b>                     | Class H per NEMA MG1-1.65  |
| <b>Standard Temperature Rise</b>             | 125°C @ Standby, 105°C @ Prime                                       |
| <b>Exciter Type</b>                          | Permanent Magnet Generator (PMG)                                     |
| <b>Phase Rotation</b>                        | A (U), B (V), C (W)  |
| <b>Alternator Cooling</b>                    | Direct drive centrifugal blower                                      |
| <b>AC Waveform Total Harmonic Distortion</b> | <5% total no load to full linear load<br><3% for any single harmonic |
| <b>Telephone Influence Factor (TIF)</b>      | <50 per NEMA MG1-22.43   |
| <b>Telephone Harmonic Factor (THF)</b>       | <3   |

| Three Phase Table <sup>1</sup>                |     | 80° C  | 80° C                  | 105° C   | 105° C                 | 125° C   | 125° C   | 125° C                | 125° C                |  |  |  |  |
|---|-----|--|------------------------|--|------------------------|--|--|-----------------------|-----------------------|--|--|--|--|
| Feature Code                                  |     | B260   | B302                   | B259   | B301                   | B258   | B252   | B246                  | B300                  |  |  |  |  |
| Alternator Data Sheet Number                  |     | 310  | 309                    | 309  | 309                    | 309  | 309  | 307                   | 308                   |  |  |  |  |
| Voltage Ranges                                |     | 110/190<br>Thru<br>139/240<br>220/380<br>Thru<br>277/480 | 347/600                | 110/190<br>Thru<br>139/240<br>220/380<br>Thru<br>277/480 | 347/600                | 110/190<br>Thru<br>139/240<br>220/380<br>Thru<br>277/480 | 120/208<br>Thru<br>139/240<br>240/416<br>Thru<br>277/480 | 277/480               | 347/600               |  |  |  |  |
| Surge kW                                      |     | 616  | 617                    | 611  | 617                    | 611  | 613  | 616                   | 619                   |  |  |  |  |
| Motor Starting kVA (at 90% sustained voltage) | PMG | 3313   | 2944                   | 2944   | 2944                   | 2944   | 2944   | 2208                  | 2429                  |  |  |  |  |
| Full Load Current - Amps at Standby Rating    |     | <u>120/208</u><br>2081                                   | <u>127/220</u><br>1968 | <u>139/240</u><br>1804                                   | <u>220/380</u><br>1139 | <u>240/416</u><br>1041                                   | <u>254/440</u><br>984                                    | <u>277/480</u><br>902 | <u>347/600</u><br>722 |  |  |  |  |

## Notes:

**1. Single Phase Capability:** Single phase power can be taken from a three phase generator set at up to 40% of the generator set nameplate kW rating at unity power factor.

## Control System

|  |  |   |   |   |   |
|--|--|---|---|---|---|
|   | <b>PowerCommand Control with AmpSentry™ Protection</b> <ul style="list-style-type: none"> <li>• The PowerCommand Control is an integrated generator set control system providing governing, voltage regulation, engine protection, and operator interface functions.</li> <li>• PowerCommand Controls include integral AmpSentry protection. AmpSentry provides a full range of alternator protection functions that are matched to the alternator provided.</li> <li>• Controls provided include Battery monitoring and testing features, and Smart-Starting control system.</li> <li>• InPower PC-based service tool available for detailed diagnostics.</li> <li>• Standard PCCNet interface. Available with Echelon LonWorks™ network interface.</li> <li>• NEMA 3R enclosure.</li> <li>• Suitable for operation in ambient temperatures from -40C to +70C, and altitudes to 13,000 feet (5000 meters).</li> <li>• Prototype tested; UL, CSA, and CE compliant.</li> </ul> |   |   |   |   |
| <b>AmpSentry AC Protection</b> <ul style="list-style-type: none"> <li>• Overcurrent and short circuit shutdown</li> <li>• Overcurrent warning</li> <li>• Single &amp; 3-phase fault regulation</li> <li>• Over and under voltage shutdown</li> <li>• Over and under frequency shutdown</li> <li>• Overload warning with alarm contact</li> <li>• Reverse power and reverse Var shutdown</li> <li>• Excitation fault</li> </ul>   | <b>Engine Protection</b> <ul style="list-style-type: none"> <li>• Overspeed shutdown</li> <li>• Low oil pressure warning and shutdown</li> <li>• High coolant temperature warning and shutdown</li> <li>• High oil temperature warning (optional)</li> <li>• Low coolant level warning or shutdown</li> <li>• Low coolant temperature warning</li> <li>• High and low battery voltage warning</li> <li>• Weak battery warning</li> <li>• Dead battery shutdown</li> <li>• Fail to start (overcrank) shutdown</li> <li>• Fail to crank shutdown</li> <li>• Redundant start disconnect</li> <li>• Cranking lockout</li> <li>• Sensor failure indication</li> </ul>   | <b>Operator Interface</b> <ul style="list-style-type: none"> <li>• OFF/MANUAL/AUTO mode switch</li> <li>• MANUAL RUN/STOP switch</li> <li>• Panel lamp test switch</li> <li>• Emergency Stop switch</li> <li>• Alpha-numeric display with pushbutton access, for viewing engine and alternator data and providing setup, controls, and adjustments</li> <li>• LED lamps indicating genset running, not in auto, common warning, common shutdown</li> <li>• (5) configurable LED lamps</li> <li>• LED Bargraph AC data display (optional)</li> </ul> |   |   |   |
| <b>Alternator Data</b> <ul style="list-style-type: none"> <li>• Line-to-line and line-to-neutral AC volts</li> <li>• 3-phase AC current</li> <li>• Frequency</li> <li>• Total and individual phase kW and kVA</li> </ul>   | <b>Engine Data</b> <ul style="list-style-type: none"> <li>• DC voltage</li> <li>• Lube oil pressure</li> <li>• Coolant temperature</li> <li>• Lube oil temperature (optional)</li> </ul>   | <b>Other Data</b> <ul style="list-style-type: none"> <li>• Genset model data</li> <li>• Start attempts, starts, running hours</li> <li>• KW hours (total and since reset)</li> <li>• Fault history</li> <li>• Load profile (hours less than 30% and hours more than 90% load)</li> <li>• System data display (optional with network and other PowerCommand gensets or transfer switches)</li> </ul>   |   |   |   |
| <b>Governing</b> <ul style="list-style-type: none"> <li>• Integrated digital electronic isochronous governor</li> <li>• Temperature dynamic governing</li> <li>• Smart idle speed mode</li> <li>• Glow plug control (some models)</li> </ul>   | <b>Voltage Regulation</b> <ul style="list-style-type: none"> <li>• Integrated digital electronic voltage regulator</li> <li>• 3-phase line to neutral sensing</li> <li>• PMG (Optional)</li> <li>• Single and three phase fault regulation</li> <li>• Configurable torque matching</li> </ul>  | <b>Control Functions</b> <ul style="list-style-type: none"> <li>• Data logging on faults</li> <li>• Fault simulation (requires InPower)</li> <li>• Time delay start and cooldown</li> <li>• Cycle cranking</li> <li>• PCCNet Interface</li> <li>• (4) Configurable customer inputs</li> <li>• (4) Configurable customer outputs</li> <li>• (8) Configurable network inputs and (16) outputs (with optional network)</li> </ul>  |   |   |   |
| <b>Options</b> <table border="1"> <tr> <td data-bbox="131 1682 581 1795"> <ul style="list-style-type: none"> <li><input type="checkbox"/> Analog AC Meter Display</li> <li><input type="checkbox"/> Thermostatically Controlled Space Heater</li> </ul> </td><td data-bbox="589 1682 1068 1795"> <ul style="list-style-type: none"> <li><input type="checkbox"/> Key-type mode switch</li> <li><input type="checkbox"/> Ground fault module</li> <li><input type="checkbox"/> Engine oil temperature</li> <li><input type="checkbox"/> Auxiliary Relays (3)</li> </ul> </td><td data-bbox="1076 1682 1565 1795"> <ul style="list-style-type: none"> <li><input type="checkbox"/> Echelon LonWorks interface</li> <li><input type="checkbox"/> Digital input and output module(s) (loose)</li> <li><input type="checkbox"/> Remote annunciator (loose)</li> </ul> </td></tr> </table> |  |   | <ul style="list-style-type: none"> <li><input type="checkbox"/> Analog AC Meter Display</li> <li><input type="checkbox"/> Thermostatically Controlled Space Heater</li> </ul> | <ul style="list-style-type: none"> <li><input type="checkbox"/> Key-type mode switch</li> <li><input type="checkbox"/> Ground fault module</li> <li><input type="checkbox"/> Engine oil temperature</li> <li><input type="checkbox"/> Auxiliary Relays (3)</li> </ul> | <ul style="list-style-type: none"> <li><input type="checkbox"/> Echelon LonWorks interface</li> <li><input type="checkbox"/> Digital input and output module(s) (loose)</li> <li><input type="checkbox"/> Remote annunciator (loose)</li> </ul> |
| <ul style="list-style-type: none"> <li><input type="checkbox"/> Analog AC Meter Display</li> <li><input type="checkbox"/> Thermostatically Controlled Space Heater</li> </ul>  | <ul style="list-style-type: none"> <li><input type="checkbox"/> Key-type mode switch</li> <li><input type="checkbox"/> Ground fault module</li> <li><input type="checkbox"/> Engine oil temperature</li> <li><input type="checkbox"/> Auxiliary Relays (3)</li> </ul>  | <ul style="list-style-type: none"> <li><input type="checkbox"/> Echelon LonWorks interface</li> <li><input type="checkbox"/> Digital input and output module(s) (loose)</li> <li><input type="checkbox"/> Remote annunciator (loose)</li> </ul>   |   |   |   |

## Generator Set Options

### Engine

- ☐ 75 A battery charging alternator
- ☐ Dual 208/240/480 V thermostatically controlled coolant heater for ambient above 40°F (4.5°C)
- ☐ Dual 208/240/480 V thermostatically controlled coolant heater for ambient below 40°F (4.5°C)
- ☐ Dual 120 V, 300 W lube oil heater
- ☐ Dual 208/240 V, 300 W lube oil heater
- ☐ Dual 480 V, 300 W lube oil heater
- ☐ Bypass oil filter
- ☐ Fuel/water separator
- ☐ Heavy-duty air cleaner with safety element

### Cooling System

- ☐ Heat exchanger cooling
- ☐ Remote radiator cooling

### Alternator

- ☐ 80°C rise alternator
- ☐ 105°C rise alternator
- ☐ 120/240 V, 300 W anti-condensation heater

### Exhaust System

- ☐ Critical-grade exhaust silencer
- ☐ Industrial-grade exhaust silencer
- ☐ Residential-grade exhaust silencer

### Generator Set

- ☐ AC entrance box
- ☐ Battery charger, equalizer, float-type
- ☐ Batteries
- ☐ Export box packaging
- ☐ Ground fault alarm
- ☐ Main line circuit breaker
- ☐ PowerCommand (3100) Digital Parallel Control
- ☐ PowerCommand Network Communication Module (NCM)
- ☐ Spring isolators
- ☐ 2-year standby warranty
- ☐ 2-year prime power warranty
- ☐ 5-year basic power warranty
- ☐ 5-year comprehensive power warranty
- ☐ 10-year major components warranty

## Available Products and Services

A wide range of products and services is available to match your power generation system requirements. Cummins Power Generation products and services include:

Diesel and Spark-Ignited Generator Sets

Transfer Switches

Bypass Switches

Parallel Load Transfer Equipment

Digital Paralleling Switchgear

PowerCommand Network and Software

Distributor Application Support

Planned Maintenance Agreements

## Warranty

All components and subsystems are covered by an express limited one-year warranty. Other optional and extended factory warranties and local distributor maintenance agreements are available. Contact your distributor/dealer for more information.

## Certifications



**ISO9001** - This generator set was designed and manufactured in facilities certified to ISO9001.



**CSA** - This generator set is CSA certified to product class 4215-01.



**PTS** - The Prototype Test Support (PTS) program verifies the performance integrity of the generator set design. Products bearing the PTS symbol have been subjected to demanding tests in accordance to NFPA 110 Level 1 to verify the design integrity and performance under both normal and abnormal operating conditions including short circuit, endurance, temperature rise, torsional vibration, and transient response, including full load pickup.



**UL** - The generator set is available Listed to UL 2200, Stationary Engine Generator Assemblies. The PowerCommand control is Listed to UL 508 - Category NITW7 for U.S. and Canadian usage.

## See your distributor for more information



**Cummins Power Generation**  
1400 73rd Avenue N.E.  
Minneapolis, MN 55432  
763.574.5000  
Fax: 763.574.5298  
[www.cumminspower.com](http://www.cumminspower.com)

Cummins and PowerCommand are registered trademarks of Cummins Inc.  
AmpSentry is a trademark of Cummins Inc.  
LonWorks is a registered trademark of Echelon

**Important:** Backfeed to a utility system can cause electrocution and/or property damage. Do not connect generator sets to any building electrical system except through an approved device or after building main switch is open.