

Model: DGFA
Frequency: 60
Fuel type: Diesel
KW rating: 150 standby
135 prime
Emissions level: EPA Nonroad Tier 1

➤ **Generator set data sheet**

Our energy working for you.™



Exhaust emission data sheet:	EDS-107
EPA Tier 1 exhaust emission compliance sheet:	
Sound performance data sheet:	MSP-111
Cooling performance data sheet:	
Prototype test summary data sheet:	PTS-106
Standard set-mounted radiator cooling outline:	0500-3121
Optional set-mounted radiator cooling outline:	
Optional heat exchanger cooling outline:	
Optional remote radiator cooling outline:	

Fuel consumption	Standby				Prime				Continuous
	kW (kVA)				kW (kVA)				kW (kVA)
Ratings	150 (188)				135 (169)				
Load	1/4	1/2	3/4	Full	1/4	1/2	3/4	Full	Full
US gph	3.2	5.8	8.3	11.1	2.9	5.3	7.6	10.0	
L/hr	12	22	31	42	11	20	29	38	

Engine	Standby rating	Prime rating	Continuous rating
Engine manufacturer	Cummins Inc.		
Engine model	6CTA8.3-G2		
Configuration	Cast iron in-line 6 cylinder		
Aspiration	Turbocharged and aftercooled		
Gross engine power output, kWm (bhp)	206.6 (277.0)	188.0 (252.0)	
BMEP at rated load, kPa (psi)	1379.0 (200.0)	1241.1 (180.0)	
Bore, mm (in)	114.0 (4.49)		
Stroke, mm (in)	135.1 (5.32)		
Rated speed, rpm	1800		
Piston speed, m/s (ft/min)	8.1 (1596.0)		
Compression ratio	16.8:1		
Lube oil capacity, L (qt)	23.8 (25.2)		
Overspeed limit, rpm	2100 ± 50		
Regenerative power, kW	22.00		

Fuel flow		
Fuel flow at rated load, L/hr (US gph)	208.2 (55.0)	
Maximum inlet restriction, mm Hg (in Hg)	101.6 (4.0)	
Maximum return restriction, mm Hg (in Hg)	254.0 (10.0)	

Air	Standby rating	Prime rating	Continuous rating
Combustion air, m ³ /min (scfm)	13.5 (478.0)	13.0 (458.0)	
Maximum air cleaner restriction w/clean filter, kPa (in H ₂ O)	2.5 (10)		
Alternator cooling air, m ³ /min (scfm)	41.3 (1460.0)		

Exhaust

Exhaust flow at rated load, m ³ /min (cfm)	36.8 (1300.0)	34.2 (1207.0)	
Exhaust temperature, °C (°F)	542.2 (1008.0)	488.3 (911.0)	
Maximum back pressure, kPa (in H ₂ O)	10.2 (41.0)		

Standard set-mounted radiator cooling

Ambient design, °C (°F)	40 (104)		
Fan load, kW (HP)	7.2 (9.6)		
Coolant capacity (with radiator), L (US gal)	28.4 (7.5)		
Cooling system air flow, m ³ /min (scfm)	212 (7486)		
Total heat rejection, MJ/min (Btu/min)	7.2 (6815)	6.5 (6093)	
Maximum cooling air flow static restriction, kPa (in H ₂ O)	0.12 (0.5)		

Optional set-mounted radiator cooling

Ambient design, °C (°F)	50 (122)		
Fan load, kW _m (HP)	7.2 (9.6)		
Coolant capacity (with radiator), L (US gal)	28.4 (7.5)		
Cooling system air flow, m ³ /min (scfm)	212 (7486)		
Total heat rejection, MJ/min (Btu/min)	7.2 (6815)	6.5 (6093)	
Maximum cooling air flow static restriction, kPa (in H ₂ O)	0.12 (0.5)		

Optional heat exchanger cooling

Set coolant capacity, L (US gal)			
Heat rejected, jacket water circuit, MJ/min (Btu/min)			
Heat rejected, after-cooler circuit, MJ/min (Btu/min)			
Heat rejected, fuel circuit, MJ/min (Btu/min)			
Total heat radiated to room, MJ/min (Btu/min)			
Maximum raw water pressure, jacket water circuit, kPa (psi)			
Maximum raw water pressure, aftercooler circuit, kPa (psi)			
Maximum raw water pressure, fuel circuit, kPa (psi)			
Maximum raw water flow, jacket water circuit, L/min (US gal/min)			
Maximum raw water flow, aftercooler circuit, L/min (US gal/min)			
Maximum raw water flow, fuel circuit, L/min (US gal/min)			
Minimum raw water flow @ 27 °C (80 °F) Inlet temp, jacket water circuit, L/min (US gal/min)			
Minimum raw water flow @ 27 °C (80 °F) Inlet temp, after-cooler circuit, L/min (US gal/min)			
Minimum raw water flow @ 27 °C (80 °F) Inlet temp, fuel circuit, L/min (US gal/min)			
Raw water delta P @ min flow, jacket water circuit, kPa (psi)			
Raw water delta P @ min flow, after-cooler circuit, kPa (psi)			
Raw water delta P @ min flow, fuel circuit, kPa (psi)			
Maximum jacket water outlet temp, °C (°F)			
Maximum after-cooler inlet temp, °C (°F)			
Maximum after-cooler inlet temp @ 25 °C (77 °F) ambient, °C (°F)			

Our energy working for you.™

www.cumminspower.com

©2008 | Cummins Power Generation Inc. | All rights reserved | Specifications subject to change without notice | Cummins Power Generation and Cummins are registered trademarks of Cummins Inc. "Our energy working for you." is a trademark of Cummins Power Generation.
D-3431 (4/08)



Optional remote radiator cooling¹

Set coolant capacity, L (US gal)	12.3 (3.3)	
Max flow rate @ max friction head, jacket water circuit, L/min (US gal/min)	208 (55)	
Heat rejected, jacket water circuit, MJ/min (Btu/min)	5.6 (5293)	5.0 (4684)
Total heat radiated to room, MJ/min (Btu/min)	1.6 (1522)	1.5 (1409)
Maximum friction head, jacket water circuit, kPa (psi)	35 (5)	
Maximum static head, jacket water circuit, m (ft)	18 (60)	
Maximum jacket water outlet temp, °C (°F)	104 (220)	100 (212)

Weights²

Unit dry weight kgs (lbs)	
Unit wet weight kgs (lbs)	1513 (3336)

Notes:

¹ For non-standard remote installations contact your local Cummins Power Generation representative.

² Weights represent a set with standard features. See outline drawing for weights of other configurations.

Derating factors

Standby	Engine power available up to 2751 m (9030 ft) at ambient temperatures up to 40 °C (104 °F). Above 2751 m (9030 ft), derate at 4% per 305 m (1000 ft), and 2% per 11 °C (1% per 10 °F) above 40 °C (104°F).
Prime	Engine power available up to 2751 m (9030 ft) at ambient temperatures up to 40 °C (104 °F). Above 2751 m (9030 ft), derate at 4% per 305 m (1000 ft), and 2% per 11 °C (1% per 10 °F) above 40 °C (104°F).
Continuous	

Ratings definitions

Emergency standby power (ESP):	Limited-time running power (LTP):	Prime power (PRP):	Base load (continuous) power (COP):
Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. Emergency Standby Power (ESP) is in accordance with ISO 8528. Fuel Stop power in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.	Applicable for supplying power to a constant electrical load for limited hours. Limited Time Running Power (LTP) is in accordance with ISO 8528.	Applicable for supplying power to varying electrical load for unlimited hours. Prime Power (PRP) is in accordance with ISO 8528. Ten percent overload capability is available in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.	Applicable for supplying power continuously to a constant electrical load for unlimited hours. Continuous Power (COP) is in accordance with ISO 8528, ISO 3046, AS 2789, DIN 6271 and BS 5514.

Our energy working for you.™

www.cumminspower.com

Alternator data

Three phase table ¹		105 °C	105 °C	105 °C	125 °C	125 °C	125 °C	125 °C	150 °C	150 °C	150 °C	
Feature code		B418	B415	B304	B417	B414	B267	B303	B416	B413	B419	
Alternator data sheet number		210	210	209	210	210	212	209	210	209	208	
Voltage ranges		110/190 thru 120/208 220/380 thru 240/416	120/208 thru 139/240 240/416 thru 277/480	347/600	110/190 thru 120/208 220/380 thru 240/416	120/208 thru 139/240 240/416 thru 277/480	120/208 thru 139/240 240/416 thru 277/480	347/600	110/190 thru 120/208 220/380 thru 240/416	120/208 thru 139/240 240/416 thru 277/480	347/600	
Surge kW		184	184	185	184	184	187	185	184	183	183	
Motor starting kVA (at 90% sustained voltage)	Shunt	563	563	516	563	563	770	516	563	516	422	
	PMG	663	663	607	663	663	920	607	663	607	497	

Full load current amps at standby rating	120/208 520	127/220 492	220/380 285	139/240 451	240/416 260	254/440 246	277/480 225	347/600 180
--	----------------	----------------	----------------	----------------	----------------	----------------	----------------	----------------

Single phase table		105 °C	105 °C	105 °C	125 °C	125 °C	125 °C	125 °C				
Feature code		B418	B415	B274	B417	B414	B273	B267				
Alternator data sheet number		210	210	212	210	210	210	212				
Voltage ranges		120/240 ²	120/240 ²	120/240 ³	120/240 ²	120/240 ²	120/240 ³	120/240 ³				
Surge kW		182	182	186	182	182	185	160				
Motor starting kVA (at 90% sustained voltage)	Shunt	330	330	420	330	330	330	420				
	PMG	385	385	500	385	385	385	500				

Full load current amps at standby rating	120/240 ² 417	120/240 ³ 625
--	-----------------------------	-----------------------------

Notes:

- ¹ Single phase power can be taken from a three phase generator set at up to 2/3 set rated 3-phase kW at 1.0 power factor. Also see Note 3 below.
- ² The broad range alternators can supply single phase output up to 2/3 set rated 3-phase kW at 1.0 power factor.
- ³ The extended stack (full single phase output) and 4 lead alternators can supply single phase output up to full set rated 3-phase kW at 1.0 power factor.

Formulas for calculating full load currents:

Three phase output

$$\frac{\text{kW} \times 1000}{\text{Voltage} \times 1.73 \times 0.8}$$

Single phase output

$$\frac{\text{kW} \times \text{SinglePhaseFactor} \times 1000}{\text{Voltage}}$$

Cummins Power Generation

1400 73rd Avenue N.E.
Minneapolis, MN 55432 USA
Phone: 763 574 5000
Fax: 763 574 5298

Warning: Back feed to a utility system can cause electrocution and/or property damage. Do not connect to any building's electrical system except through an approved device or after building main switch is open.

Our energy working for you.™

www.cumminspower.com